

# MR108 MRseries MR108A

Two-way Loudspeaker System




MR108 is a compact, small size, coaxial, 2-way full range monitor speaker, has balanced and real sound quality. Configuration:1x8" high efficency midbass unit and 1x1" exit throat 44mm voice coil HF driver with horn make up the coaxial. The cabinet is made of multilayer composite plywood with wear-resistant polyurea paint. MR108A is equipped with digital amplifier based on MR108 to be an active speaker.

MR108 是一款8"同轴两分频全频监听音箱,结构紧凑,体积小,音质平衡、真实。单元配置:1只8"高效率中低音单元和1只1"喉口44芯驱动器加号角组成同轴。箱体采用多层复合夹板,耐磨聚脲喷涂。MR108A是在MR108的基础上配置D类功放的有源音箱。



## CONFIGURATION





#### ----

MODEL FREQUENCY RESPONSE(-3dB) FREQUENCY RESPONSE(-10dB) DRIVERS

RATED POWER
SENSITIVITY
MAXIMUM SPL
IMPEDANCE
DISPERSION(-6dB)
CROSSOVER FREQUENCIES
INPUT CONNECTORS
PACKAGE SIZE
NET WEIGHT
GROSS WEIGHT

MR108

90Hz-18KHz

85Hz-20KHz

 $1\times8"$ (200mm)/ 2"voice coil LF

 $1\times1"$ (25mm) / 1.4"voice coil HF

150W RMS,600W peak

95dB 1watt/1 metre

116dB continuous,122dB peak

8 ohms nominal

90° × 90°

2.2kHz passive

2×Speakon NL4

420mm $\times 345$ mm $\times 425$ mm

10 kg/pc

12 kg/pc

#### **FEATURES**

- High quality coaxial design
- Small size, light weight
- Can be placed on stage, can be hung
- Applications: Stage monitor

### 产品特征

- ●高品质同轴结构设计
- ●体积小、重量轻
- ●可舞台摆放、可吊挂

## 适用范围

●舞台监听

MR108A

90Hz-18KHz

85Hz-20KHz

1×8"(200mm)/ 2"voice coil LF

 $1\times1"$ (25mm) / 1.4"voice coil HF

300W/8Ω

116dB continuous,122dB peak

90° ×90°

\_

INPUT TYPE: Balanced Differential line

 $420mm \times 345mm \times 425mm$ 

12 kg/pc

14 kg/pc

www.fdbaudio.com Page 28